

Power (kW)	Domain		Architecture			Configuration							Provisional Suffix	
04	A	Exclusively Domestic Exclusively Indoor	1	Internal Protection Internal Trip	-	From 00 to FF	0	0	0	0	0	0	No specificity	From 00 TO FF Further categorization provision
07	B	Exclusively Domestic Indoor and Outdoor	2	External Protection Internal Trip			x	x	x	x	x	1	Multi Charging (or submetering)	
11	C	Other products Exclusively Indoor	3	Internal Protection External Trip			x	x	x	x	1	x	Back office communication	
22	D	Other products Indoor and Outdoor	4	External Protection External Trip			x	x	x	1	x	x	Energy management	
>=43							x	x	1	x	x	x	RFID or other identification	
							x	1	x	x	x	x	Configurable product (locally, remote)	
							1	x	x	x	x	x	Surge protection	

Classification of Charging Station related to Installation Qualification Level	Domain of Intervention	Complexity	Installation Qualification Level (*)
<p><b>P1:</b> Station less than 11kVA including 11kVA, single charging point and no configuration likely to generate additional installation constraints</p> <p><b>P D A C</b> (Product/Domain/Architecture/Configuration)</p> <p>-----</p> <p>04 A 1 00; 04; 20; 24 07 B 2 11</p>	<p><b>D1:</b> Home and small tertiary and Icc =&lt; 6kA</p>	<p><b>C1:</b> Calculation note and specific tools not required EV-Ready Tool or equivalent required</p>	<p><b>Q1:</b> basic training for the installation of simplest products</p>
<p><b>P2:</b> Station up to 22kVA including 22kVA, any application (home or B2B), any configuration (simple or multiple)</p> <p><b>P D A C</b> (Product/Domain/Architecture/Configuration)</p> <p>-----</p> <p>04 A 1 00 to FF 07 B 2 11 C 3 22 D 4</p>	<p><b>D2:</b> Residential and office buildings, condominium, professional and industrial or Icc &gt; 6kA</p>	<p><b>C2:</b> Basic calculation note, loop ground line measurer and installation tester required</p>	<p><b>Q2:</b> Specific training for intermediate complexity products</p>
<p><b>P3:</b> all other stations including Fast charge</p> <p><b>P D A C</b> (Product/Domain/Architecture/Configuration)</p> <p>-----</p> <p>04 A 1 00 to FF 07 B 2 11 C 3 22 D 4 &gt;=43</p>	<p><b>D3:</b> Roads and + public acces</p>	<p><b>C3:</b> Calculation note and any necessary tools</p>	<p><b>Q3:</b> Expert training for high complexity products and public configuration</p>
*	<p><b>Q1</b> --&gt; Limited to P1, D1, C1  <b>Q2</b> --&gt; Required if P2 or D2 or C2, and no level &gt;2  <b>Q3</b> --&gt; Required if at least one classification P or D or C is level 3</p>		